




Through Coupler Panel 16 Port RJ45 to Telco



- 16 E1 channels
- 16 RJ45s to 2 Telcos
- 1 x Receive Telco 1 x Transmit Telco
- 19 inch 1U rack mount
- Wiring as per Cisco 72-5184-01, Tyco 2163442-1
- Available with Cisco 0-15, or standard 1-16 numbering scheme
- Interconnects Cisco ASR903 Routers to Alcatel 1151 MAX-C
- Manufactured on the Isle of Man, Great Britain

Specifications	
Connectors	16 x RJ45 female shielded 2 x Telco female shielded
Materials	Case - Zintec, black powder coated
Power Requirements	No power required
Dimensions (W x H x D)	482 x 44 x 60 mm.
Weight	1.25 kg.
Warranty	10 Years, parts and labour
Conformance	2002/95/EC RoHS EN60950-1:2006 (ed.2) + A11:2009 2004/108/EC Electromagnetic Compatibility. RTTE Directive. Safety Directive as a SELV component. UL listed 56Y4 and rated UL 94V-0 CE
Harmonisation/TARIC Code	8544 – 421000

Tekmos Communications Limited - www.tekmos.co.uk

Tekmos Communications Limited
The Tower, Gladstone Park Ind. Est.
Ramsey, Isle of Man, IM8 2LA, GB
Phone: +44 (0)1624 818 275
Fax: +44 (0)1624 818 274

Title Through Coupler Panel 16 Port RJ45 to Telco
Part Number TK-UTC45-016-TTR
Page 1 of 2

Wiring Scheme

Port	Tx Signal	Pin		RJ45 Pin		Pin	Rx Signal
0\1	Tx Tip P1	14	-	2 5	-	14	Rx Tip P1
	Tx Ring P1	39	-	1 4	-	39	Rx Ring P1
1\2	Tx Tip P2	13	-	2 5	-	13	Rx Tip P2
	Tx Ring P2	38	-	1 4	-	38	Rx Ring P2
2\3	Tx Tip P3	10	-	2 5	-	10	Rx Tip P3
	Tx Ring P3	35	-	1 4	-	35	Rx Ring P3
3\4	Tx Tip P4	9	-	2 5	-	9	Rx Tip P4
	Tx Ring P4	34	-	1 4	-	34	Rx Ring P4
4\5	Tx Tip P5	16	-	2 5	-	16	Rx Tip P5
	Tx Ring P5	41	-	1 4	-	41	Rx Ring P5
5\6	Tx Tip P6	15	-	2 5	-	15	Rx Tip P6
	Tx Ring P6	40	-	1 4	-	40	Rx Ring P6
6\7	Tx Tip P7	12	-	2 5	-	12	Rx Tip P7
	Tx Ring P7	37	-	1 4	-	37	Rx Ring P7
7\8	Tx Tip P8	11	-	2 5	-	11	Rx Tip P8
	Tx Ring P8	36	-	1 4	-	36	Rx Ring P8
8\9	Tx Tip P9	6	-	2 5	-	6	Rx Tip P9
	Tx Ring P9	31	-	1 4	-	31	Rx Ring P9
9\10	Tx Tip P10	5	-	2 5	-	5	Rx Tip P10
	Tx Ring P10	30	-	1 4	-	30	Rx Ring P10
10\11	Tx Tip P11	2	-	2 5	-	2	Rx Tip P11
	Tx Ring P11	27	-	1 4	-	27	Rx Ring P11
11\12	Tx Tip P12	1	-	2 5	-	1	Rx Tip 12
	Tx Ring P12	26	-	1 4	-	26	Rx Ring 12
12\13	Tx Tip P13	8	-	2 5	-	8	Rx Tip P13
	Tx Ring P13	33	-	1 4	-	33	Rx Ring P13
13\14	Tx Tip P14	7	-	2 5	-	7	Rx Tip P14
	Tx Ring P14	32	-	1 4	-	32	Rx Ring P14
14\15	Tx Tip P15	4	-	2 5	-	4	Rx Tip P15
	Tx Ring P15	29	-	1 4	-	29	Rx Ring P15
15\16	Tx Tip P16	3	-	2 5	-	3	Rx Tip P16
	Tx Ring P16	28	-	1 4	-	28	Rx Ring P16

Tekmos Communications Limited - www.tekmos.co.uk

Tekmos Communications Limited
The Tower, Gladstone Park Ind. Est.
Ramsey, Isle of Man, IM8 2LA, GB
Phone: +44 (0)1624 818 275
Fax: +44 (0)1624 818 274

Title Through Coupler Panel 16 Port RJ45 to Telco
Part Number TK-UTC45-016-TTR
Page 2 of 2